
TECHNICAL INFORMATION

SENTRY G3



PREDICTIVE MAINTENANCE SYSTEMS

G3 - VAM VIBRATION ANALYSIS MODULE



- Time and FFT Data Capture
- Order Locked Analysis
- 16 / 32 dynamic channels
- Up to 8 phase reference channels
- Dual TCP/IP interface
- Fits Slot 6 Sentry G3 Rack
- SD Card Storage for Dynamic data

The Sentry G3 Vibration Analysis Module is designed to acquire transient analysis data from up to 32 dynamic channels across two G3 rack systems. The module is located in slot 6 of the G3 master rack and connects to the G3 monitor modules through the rack backplane, connecting to the secondary slave rack backplane through a multi-way cable assembly.

Order locked time data and asynchronous FFT's are acquired by the module according to the phase reference allocation and module configuration. All data is communicated via TCPIP for storage on a local server and PC based software is utilised to access the data to perform the required offline analysis of the data files. Internal Flash storage is utilised within the module for capturing pre and post static and transient data on alarm.

The separate SentryG3 VAM hardware concept ensures the protection element of the machine monitoring system is separate and diverse from the analysis acquisition and associated software tools.

Acquisition modes and the alarm configurations are programmed directly to the Sentry VAM module through the remote user interface. Other plant data can be captured and trended through both OPC and TCPIP Modbus protocols to the Server.

G3 - VAM

TECHNICAL SPECIFICATION

HΑ	п	_	1 A	,,	n	_
НΔ	ĸ		w	ľĽ	ĸ	-

Number of Channels Max 32 channels

256 kHz sampling

Transducer Select Accelerometer

Velocity Transducer Proximity Probe

Accelerometer Sensitivity 10.00mV/g to 1.0V/g

Velocity Sensitivity 1mV/mm/s to

50mV/mm/s

Proximity probe Sensitivity 3.94mV/um or

7.84mV/um

Proximity probe gap range -20.0V to -0.1V

Dynamic Range -20.0V to +20.0V

Resolution 24-bit

Phase Reference Up to 8 Channels

TTL from G3 rack or

auxiliary bus

Acquisition Simultaneous parallel

acquisition and asynchronous

acquisition via FFT in

all modes.

Synchronous Acquisition

Modes

Delta RPM Delta Time On Alarm

Synchronous Waveform 128 samples / rev

Sampling Rates 16 revolution average

64 samples / rev 32 revolution average

32 samples / rev 16 revolution average

Synchronous Measurements Magnitude and Phase

Order 1 - 100

Sub-synchronous and Non-synchronous levels available through analysis

software

FFT Resolution 800 line Spectrum

Up to 4000Hz

Frequency Range all with Anti-Alias

Filtering

FFT Acquisition Modes Delta RPM

Delta Time

Online Delta Time

Alarm Data Collection of static

and dynamic data internal to module for user defined pre and

post period.

Available Memory 32GByte

Rack Communication KANBUS for collection

of protection module settings, alarms and

static values.

Module Set Up Configuration of the

module is carried out through the TCPIP interface utilising the

SentryCMS application.

SOFTWARE

SentryCMS SW for Windows 64-bit

Software Analysis Options

- 1. Bode Plot, Amplitude versus RPM or Time
- 2. Polar Plot
- 3. FFT Waterfall, Z-axis time
- 4. Orbit Plot, X&Y
- 5. Shaft Centreline
- 6. Multi-Parameter trending versus time
- 7. Bar Graph
- 8. Text data format
- 9. Synchronous and Asynchronous analysis

Alarms when in Online Mode

- 1. Overall Vibration / magnitude Change
- 2. Phase Change
- 3. Harmonics
- 4. Defined Frequency bands
- 5. FFT bands
- 6. Acceptance region

Time Synchronisation through TCPIP Network

LAN

Ethernet 10/100 Mbps, RJ45, Auto MDI/MDIX, dual port

Protection Built-in 1.5KV magnetic isolation

Power Consumption

250mA max, 24Vdc, through rack +24V backplane power supply

Front Panel Indicators

ON – Indicates green when module is correctly powered on. Power supply fault results in LED turning off.

LINK – Indicates green when the unit is operating correctly. Off indicates faulty module.

TxD RxD – Flashes green when communicating data through TCPIP either direction.

ERROR – Indicates red when the unit is in error or an IP conflict. Indicates red while module booting on power up.

Alarm Relays

PSU OK Normally energised, non-latching, change over contacts COMMS OK Normally energised, non-latching, change over contacts

Both SPST configuration (250VAC / 1A)

Temperature

Operating $-20^{\circ}\text{C to } +65^{\circ}\text{C}$ Storage $-30^{\circ}\text{C to } +65^{\circ}\text{C}$

DS1260



Sensonics Ltd Northbridge Road Berkhamsted Herts, HP4 1EF United Kingdom Tel: +44 (0)1442 876833 Fax: +44 (0)1442 876477

www.sensonics.co.uk